# Product data sheet Characteristics

# **XACB4915**

# pendant station XAC-B - 4 pushbuttons + 1 emergency stop - power circuit - 12 A



#### Main

Range of product	Harmony XAC
Product or component type	Pendant control station
Device short name	XACB

## Complementary

Enclosure material	Glass reinforced polyester					
Electrical circuit type	Power circuit					
Enclosure type	Ready for use enclosure					
Control station application	Control of single speed hoist motor					
Control station composition	4 push-buttons + 1 emergency stop					
Control button type	Emergency stop push-button Ø 40 mm 3 NC trigger action First push-button 2-pole raise, slow Second push-button 2-pole lower, slow Fourth push-button 2-pole left, slow Third push-button 2-pole right, slow					
Product compatibility	XESD1191 for reversing operation XACS3991 for emergency stop					
Mechanical interlocking	With mechanical interlocking between pairs					
Control station colour	Yellow					
Connections - terminals	Screw clamp terminals, 1 x 2.5 mm <sup>2</sup> with or without cable end Screw clamp terminals, 2 x 1.5 mm <sup>2</sup> with or without cable end					
Standards	EN/ISO 13850: 2006 CSA C22.2 No 14 EN/IEC 60204-32 EN/IEC 60947-5-1 EN/IEC 60947-5-5					
Product certifications	CSA					
Protective treatment	TH					
Ambient air temperature for operation	-2570 °C					
Ambient air temperature for storage	-4070 °C					
Vibration resistance	15 gn (f= 10500 Hz) conforming to IEC 60068-2-6					
Shock resistance	100 gn conforming to IEC 60068-2-27					
Overvoltage category	Class II conforming to IEC 61140					
IP degree of protection	IP65 conforming to IEC 60529					
IK degree of protection	IK08					
Mechanical durability	1000000 cycles					
Cable entry	Rubber sleeve with stepped entry 1022 mm					
[Ithe] conventional enclosed thermal current	12 A					
[Ui] rated insulation voltage	Emergency stop contact: 400 V (pollution degree 3) conforming to IEC 60947-1 600 V conforming to CSA					
[Uimp] rated impulse withstand voltage	6 kV conforming to IEC 60947-1					
Contact operation	Snap action					

Operating force	17 N push-button 40 N emergency stop				
Short-circuit protection	10 A fuse protection by cartridge fuse type aM				
Rated power in hp	2 Hp at 240 V, CSA certified 3 Hp at 600 V, CSA certified 5 hp at 400 V, CSA certified				
Rated operational power in W	2200 W AC-3 at 240 V conforming to IEC 60947-3 appendix A 2200 W AC-3 at 400 V conforming to IEC 60947-3 appendix A 2200 W AC-4 at 240 V conforming to IEC 60947-3 appendix A 2200 W AC-4 at 400 V conforming to IEC 60947-3 appendix A				
Electrical durability	300000 Cycles AC-3, 2200 W at 240 V, operating rate <10 cyc/mn, load factor = 0.4 conforming to IEC 60947-3 appendix A 300000 Cycles AC-3, 2200 W at 400 V, operating rate <10 cyc/mn, load factor = 0.4 conforming to IEC 60947-3 appendix A 300000 Cycles AC-4, 2200 W at 240 V, operating rate <10 cyc/mn, load factor = 0.4 conforming to IEC 60947-3 appendix A 300000 Cycles AC-4, 2200 W at 400 V, operating rate <10 cyc/mn, load factor = 0.4 conforming to IEC 60947-3 appendix A 500000 Cycles AC-3, 1500 W at 240 V, operating rate <10 cyc/mn, load factor = 0.4 conforming to IEC 60947-3 appendix A 500000 Cycles AC-4, 1500 W at 240 V, operating rate <10 cyc/mn, load factor = 0.4 conforming to IEC 60947-3 appendix A 800000 Cycles AC-3, 1500 W at 400 V, operating rate <10 cyc/mn, load factor = 0.4 conforming to IEC 60947-3 appendix A 800000 cycles AC-4, 1500 W at 400 V, operating rate <10 cyc/mn, load factor = 0.4 conforming to IEC 60947-3 appendix A				
Terminals description ISO n°1	(23-24)NO (43-44)NO (33-34)NO (13-14)NO				
Terminals description ISO n°2	(21-22)NC (31-32)NC (11-12)NC				
Terminal identifier	(13-14)NO (11-12)NC				
Net weight	1.26 kg				

# Offer Sustainability

REACh Regulation	☑ REACh Declaration					
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)					
Mercury free	Yes					
China RoHS Regulation	China RoHS Declaration					
RoHS exemption information	₫Yes					
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins					
California proposition 65	WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov					


## Contractual warranty

· · · · · · · · · · · · · · · · · · ·		
	Warranty	10 mantha
Warranty 18 months	warraniv	TO MODULIS
Transact,		

# Product data sheet Dimensions Drawings

#### **Dimensions**

Below drawing shows a product with 6 cut-outs. Select the number of cut-outs according to the product characteristics in order to get b, b1 and c dimensions.



## (1) With mushroom head operator


#### Dimensions in mm

Number of cut-outs	2	4	6	8	12
b	409	499	589	679	679
b1	220	310	400	490	490
С	98	98	98	98	98
d	40	40	40	40	30

#### Dimensions in in.


Number of cut-outs	2	4	6	8	12
b	16.10	19.64	23.19	26.73	26.73
b1	8.66	12.20	15.75	19.29	19.29
С	3.86	3.86	3.86	3.86	3.86
d	1.57	1.57	1.57	1.57	1.18

#### Protective cable sleeves




# **Protective Guard**

## **Dimensions**



## Control of Single-Speed Reversing Motor 2-Phase Switching

With XESD1191 contact block, to be ordered separately



Combined with 3-pole isolating block XACS399 or XACS3991, shown in the unoperated position (pendant station "supplied"), fitted with key release trigger action latching Emergency stop operator.

