### XVEL34

## Complete illuminated beacon, Harmony XVE Optimum, red steady 5 watt or led 240 V max



Main	
Range of product	Harmony XVE Optimum
Product or component type	Complete illuminated beacon
Beacon or indicator bank unit type	base unit     illuminated unit     screw fixing cover     short fixing base
Signalling type	Steady
Component name	XVE
Light source	Bulb not included, red
Bulb type	Incandescent with BA 15d base

<= 240 V AC/DC

#### Complementary

Mounting diameter	70 mm
Maximum power dissipation in W	5 W
Connections - terminals	Screw clamp terminals, <= 1 x 1.5 mm² with cable end
Marking	CE
[Ui] rated insulation voltage	250 V conforming to IEC 60947-1
Nominal voltage limit	0.851.1 Un conforming to IEC 60947-5-1
[Uimp] rated impulse withstand voltage	4 kV conforming to IEC 60947-1
Luminance	640 cd/m²
CAD overall width	70 mm
CAD overall height	129 mm
CAD overall depth	70 mm
Terminals description ISO n°1	(COM-1)PW (GND)GROUND
Net weight	0.245 kg

[Us] rated supply volt-

#### Environment

2.17.1.01.11.01.11		
Standards	EN/IEC 60947-1 EN/IEC 60947-5-1	
Product certifications	UL[RETURN]CSA[RETURN]CCC	
Ambient air temperature for storage	-4070 °C	
Ambient air temperature for operation	-2555 °C	
Electrical shock protection class	Class I aluminium tube mounting conforming to IEC 61140 Class I plastic tube mounting conforming to IEC 61140	
Protective treatment	TC	
IP degree of protection	IP40 any position except vertical position conforming to IEC 60529 IP42 vertical position conforming to IEC 60529	

#### **Packing Units**

PCE	
1	
7 cm	
14.5 cm	
7 cm	
245 g	
-	1 7 cm 14.5 cm 7 cm


Warranty 18 months

# Product data sheet Dimensions Drawings

## XVEL34

#### Illuminated Beacon

#### Dimensions






# Product data sheet Mounting and Clearance

## XVEL34

#### Illuminated Beacon

Panel Cut-out for Mounting Directly on Fixing Base





## Product data sheet Connections and Schema

## XVEL34

#### Illuminated Beacon

### Wiring Diagram

