

Product data sheet Characteristics

LU9MR1

control terminal block - for reversing motor starter TeSys U



Main		
Range	TeSys	
Device short name	LU9MR	
Product or component type	Control terminal block	
Product compatibility	LU6MB0	

Complementary

Net weight	0.03 kg
Tightening torque	Control circuit: 0.81.2 N.m flat screwdriver 5 mm Control circuit: 0.81.2 N.m Philips No 2 screwdriver 5 mm Power circuit: 1.92.5 N.m flat screwdriver 6 mm Power circuit: 1.92.5 N.m Philips No 2 screwdriver 6 mm Power circuit: 1.92.5 N.m pozidriv No 2 screwdriver 6 mm
	<u>'</u>

Packing Units

Unit Type of Package 1	PCE	
Number of Units in Package 1	1	
Package 1 Height	3.0 cm	
Package 1 Width	3.5 cm	
Package 1 Length	5.0 cm	
Package 1 Weight	26.0 g	
Unit Type of Package 2	S01	
Number of Units in Package 2	30	
Package 2 Height	15.0 cm	
Package 2 Width	15.0 cm	
Package 2 Length	40.0 cm	
Package 2 Weight	970.0 g	

Offer Sustainability

REACh Regulation	REACh Declaration
REACh free of SVHC	Yes
EU RoHS Directive	Compliant EEU RoHS Declaration
Toxic heavy metal free	Yes
Mercury free	Yes
China RoHS Regulation	China RoHS Declaration
RoHS exemption information	₽¥Yes
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not inherenced as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the documentation is not be used to perform the appropriate and complete risk analysis, evaluation of the products with respect to the relevant specific application or use thereof. Neither Schmeider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

Warranty 18 months