


Product data sheet Characteristics

XCKD2101G11

limit switch XCKD - with rotary head w/o operating lever - 1NC+1NO - snap - Pg11





Main

Telemecanique Limit switches XC Standard
Standard format
Limit switch
XCKD
Compact
Fixed
Rotary head
Metal
Zamak
Zamak
By the body
Rotary
Spring return without operating lever
Lateral approach, 2 directions
2
1 NC + 1 NO
Snap action

Complementary

Complementary	
Electrical connection	Screw-clamp terminals, clamping capacity: 1 x 0.342 x 1.5 mm ²
Cable entry	1 entry tapped for Pg 11 cable gland
Contacts insulation form	Zb
Positive opening	With
Positive opening minimum torque	0.25 N.m
Minimum torque for tripping	0.1 N.m
Maximum actuation speed	1.5 m/s
Contact code designation	A300, AC-15 (Ue = 240 V), Ie = 3 A, Ithe = 10 A conforming to EN 60947-5-1 A300, AC-15 (Ue = 240 V), Ie = 3 A, Ithe = 10 A conforming to IEC 60947-5-1 appendix A Q300, DC-13 (Ue = 250 V), Ie = 0.27 A conforming to EN 60947-5-1 Q300, DC-13 (Ue = 250 V), Ie = 0.27 A conforming to IEC 60947-5-1 appendix A
[Ui] rated insulation voltage	300 V conforming to UL 508 500 V (pollution degree 3) conforming to IEC 60947-1 300 V conforming to CSA C22.2 No 14
Maximum resistance across terminals	25 MOhm conforming to IEC 60255-7 category 3
[Uimp] rated impulse withstand voltage	6 KV conforming to IEC 60664 6 kV conforming to IEC 60947-1
Short-circuit protection	10 A cartridge fuse, type gG
Electrical durability	5000000 Cycles, DC-13, 120 V, 4 W, operating rate <60 cyc/mn, load factor: 0.5 conforming to IEC 60947-5-1 appendix C 5000000 Cycles, DC-13, 24 V, 10 W, operating rate <60 cyc/mn, load factor: 0.5 conforming to IEC 60947-5-1 appendix C 5000000 cycles, DC-13, 48 V, 7 W, operating rate <60 cyc/mn, load factor: 0.5 conforming to IEC 60947-5-1 appendix C
Mechanical durability	10000000 cycles

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not inherent or and is not to be used for determining suitability or inhability of these products for specific user applications. It is the dourn aren in integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

Width	31 mm
Height	65 mm
Depth	30 mm
Net weight	0.185 kg
Terminals description ISO n°1	(13-14)NO (21-22)NC

Environment

50 gn for 11 ms conforming to IEC 60068-2-27
25 gn (f= 10500 Hz) conforming to IEC 60068-2-6
IP66 conforming to IEC 60529 IP67 conforming to IEC 60529
IK06 conforming to EN 50102
Class I conforming to IEC 61140 Class I conforming to NF C 20-030
-2570 °C
-4070 °C
TC
UL[RETURN]CCC[RETURN]CSA
EN 60947-5-1 IEC 60947-5-1 EN 60204-1 CSA C22.2 No 14 UL 508 IEC 60204-1

Packing Units

1 doking office	
Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	3.2 cm
Package 1 Width	4.0 cm
Package 1 Length	9.8 cm
Package 1 Weight	191.0 g
Unit Type of Package 2	S01
Number of Units in Package 2	44
Package 2 Height	15 cm
Package 2 Width	15 cm
Package 2 Length	40 cm
Package 2 Weight	8.629 kg

Offer Sustainability

Sustainable offer status	Green Premium product
REACh Regulation	☑ REACh Declaration
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
Mercury free	Yes
RoHS exemption information	₫Yes
Circularity Profile	No need of specific recycling operations


Contractual warranty

Warranty	18 months
----------	-----------

Product data sheet **Dimensions Drawings**

XCKD2101G11

Dimensions




- Tapped entry for Pg 11 cable gland
- 2 elongated holes \emptyset 4.3 x 6.3 mm on 22 mm centres, 2 holes \emptyset 4.3 on 20 mm centres. 2 x \emptyset 3 holes for support studs, depth 4 mm.
- (2)

XCKD2101G11

Mounting with Cable Entry

Position of Cable Gland






- (1) Recommended
- (2) To be avoided

Mounting with Rotary Heads and Levers


Type of Cam





- (1) Recommended
- (2) To be avoided

Setting-up with Head ZCE01 and ZCE09



- (1) Tightening torque (Min: 1) (Max: 1.5)
- (2) Tightening torque (Min: 0.8) (Max: 1.2)

Wiring Diagram

2-pole NC + NO Snap Action



Product data sheet **Technical Description**


XCKD2101G11

Characteristics of Actuation

Switch Actuation on End



Functionnal Diagram



- Closed
- Open
- (4) (5)
- Tripping Resetting