

Product data sheet Characteristics

ZB5AA331 Push button head, plastic, flush, green, Ø22, spring return, marked I





Main

Wichti	
Range of product	Harmony XB5
Product or component type	Head for non-illuminated push-button
Device short name	ZB5
Bezel material	Dark grey plastic
Mounting diameter	22 mm
Head type	Standard
Sale per indivisible quantity	1
Shape of signaling unit head	Round
Type of operator	Spring return
Operator profile	Green flush, I (white)

Complementary

Device presentation	Basic element	
	SR1 for <3 contacts using single blocks in rear mounting	
	SF1 for <3 contacts using single blocks in front mounting	
	C15 for <1 contacts using single blocks in nort mounting	
	C11 for <3 contacts using single and double blocks in nont mounting	
	C2 for <9 contacts using single blocks in non mounting C2 for <9 contacts using single and double blocks in front mounting	
Electrical composition code	C1 for <9 contacts using single blocks in front mounting	
	XALK 25 cut-outs	
Station name	XALD 15 cut-outs	
Mechanical durability	10000000 cycles	
Net weight	0.018 kg	
CAD overall depth	28 mm	
CAD overall height	29 mm	
CAD overall width	29 mm	
Complementary		

Environment

Protective treatment	ТН		
Ambient air temperature for storage	-4070 °C		
Ambient air temperature for operation	-4070 °C		
Overvoltage category	Class II conforming to IEC 60536		
IP degree of protection	IP66 conforming to IEC 60529 IP67 IP69 IP69K		
NEMA degree of protection	NEMA 13 NEMA 4X		
Resistance to high pressure washer	7000000 Pa at 55 °C, distance : 0.1 m		
IK degree of protection	IK03 conforming to IEC 50102		

Standards	CSA C22.2 No 14		
	JIS C8201-5-1		
	IEC 60947-5-1		
	IEC 60947-5-4		
	UL 508		
	IEC 60947-1		
	JIS C8201-1		
Product certifications	DNV[RETURN]LROS (Lloyds register of shipping)[RETURN]BV[RETURN]UL listed[RETURN]GL[RETURN]CSA		
Shock resistance	30 gn (duration = 18 ms) for half sine wave acceleration conforming to IEC 60068-2-27		
	50 gn (duration = 11 ms) for half sine wave acceleration conforming to IEC 60068-2-27		
Vibration resistance	5 gn (f= 2500 Hz) conforming to IEC 60068-2-6		

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	3.400 cm
Package 1 Width	4.300 cm
Package 1 Length	5.300 cm
Package 1 Weight	17.000 g
Unit Type of Package 2	S03
Number of Units in Package 2	300
Package 2 Height	30.000 cm
Package 2 Width	30.000 cm
Package 2 Length	40.000 cm
Package 2 Weight	5.497 kg
Unit Type of Package 3	P06
Number of Units in Package 3	2400
Package 3 Height	75.000 cm
Package 3 Width	80.000 cm
Package 3 Length	60.000 cm
Package 3 Weight	51.976 kg

Offer Sustainability

Sustainable offer status	Green Premium product			
REACh Regulation	REACh Declaration			
REACh free of SVHC	Yes			
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)			
Toxic heavy metal free	Yes			
Mercury free	Yes			
China RoHS Regulation	China RoHS Declaration			
RoHS exemption information	₽¥Yes			
Environmental Disclosure	Product Environmental Profile			
Circularity Profile	End Of Life Information			


Contractual warranty

Warranty

18 months

Product data sheet Dimensions Drawings ZB5AA331


Dimensions



Panel Cut-out for Pushbuttons, Switches and Pilot Lights (Finished Holes, Ready for Installation)

ZB5AA331

Connection by Screw Clamp Terminals or Plug-in Connectors or on Printed Circuit Board




(1) Diameter on finished panel or support

(2) For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended.

(3) Ø22.5 mm recommended (Ø22.3 $_0$ ^{+0.4}) / Ø0.89 in. recommended (Ø0.88 in. $_0$ ^{+0.016})

Connections	a in mm	a in in.	b in mm	b in in.
By screw clamp terminals or plug-in connector	40	1.57	30	1.18
By Faston connectors	45	1.77	32	1.26
On printed circuit board	30	1.18	30	1.18

Detail of Lug Recess



(1) Diameter on finished panel or support

(2) For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended.

(3) Ø22.5 mm recommended (Ø22.3 $_0$ ^{+0.4}) / Ø0.89 in. recommended (Ø0.88 in. $_0$ ^{+0.016})

Pushbuttons, Switches and Pilot Lights for Printed Circuit Board Connection

Panel Cut-outs (Viewed from Installer's Side)



A: 30 mm min. / 1.18 in. min. B: 40 mm min. / 1.57 in. min.

Printed Circuit Board Cut-outs (Viewed from Electrical Block Side)

Dimensions in mm



A: 30 mm min. B: 40 mm min.

Dimensions in in.



A: 1.18 in. min. B: 1.57 in. min.

General Tolerances of the Panel and Printed Circuit Board

The cumulative tolerance must not exceed 0.3 mm / 0.012 in.: T1 + T2 = 0.3 mm max.

Installation Precautions

- Minimum thickness of circuit board: 1.6 mm / 0.06 in.
- Cut-out diameter: 22.4 mm ± 0.1 / 0.88 in. ± 0.004
- Orientation of body/fixing collar ZB5AZ009: ± 2°30' (excluding cut-outs marked a and b).
- Tightening torque of screws ZBZ006: 0.6 N.m (5.3 lbf.in) max.
- Allow for one ZB5AZ079 fixing collar/pillar and its fixing screws:
 - every 90 mm / 3.54 in. horizontally (X), and 120 mm / 4.72 in. vertically (Y).
 - with each selector switch head (ZB5AD•, ZB5AJ•, ZB5AG•).

The fixing centers marked a and b are diagonally opposed and must align with those marked 4 and 5.




Mounting of Adapter (Socket) ZBZ01•


- 1 2 elongated holes for ZBZ006 screw access
- 2 1 hole Ø 2.4 mm \pm 0.05 / 0.09 in. \pm 0.002 for centring adapter ZBZ01•
- 38 × Ø 1.2 mm / 0.05 in. holes
- 4 1 hole Ø 2.9 mm ± 0.05 / 0.11 in. ± 0.002, for aligning the printed circuit board (with cut-out marked a)
- 5 1 elongated hole for aligning the printed circuit board (with cut-out marked b)
- 6 4 holes Ø 2.4 mm / 0.09 in. for clipping in adapter ZBZ01•

Dimensions An + 18.1 relate to the Ø 2.4 mm ± 0.05 / 0.09 in. ± 0.002 holes for centring adapter ZBZ01•.

Electrical Composition Corresponding to Code C1



Electrical Composition Corresponding to Code C2



Electrical Composition Corresponding to Codes C9, C11, SF1 and SR1

Electrical Composition Corresponding to Code C15

1 N/O

1 N/C

Legend

Single contact

Double contact

Light block

Possible location