

## Product data sheet Characteristics

## ZB5AFDD key-operated pushbutton head Ø22 push-turn release Dom 4A185



	main			
	Range of product	Harmony XB5		
	Product or component type	Head for non-illuminated push-button		
	Device short name	ZB5		
	Bezel material	Dark grey plastic		
	Mounting diameter	22 mm		
	Head type	Standard		
	Sale per indivisible quantity	1		
	Shape of signaling unit head	Round		
	Type of operator	Turn to release		
	Operator profile	Key switch		
	Type of keylock	Dom 4A185		
	Key withdrawal position	Both positions		
	Locking position	Actuated position		
Complementary				
CAD overall width	29 mm			
CAD overall height	29 mm			
CAD overall depth	62 mm			
Net weight	0.05 kg			
Mechanical durability	500000 cycles			
Station name	XALD 15 cut-outs XALK 25 cut-outs			
Electrical composition code	C12 for <6 contacts using single blocks in front mounting C15 for <1 contacts using single blocks in front mounting SF1 for <3 contacts using single blocks in front mounting SR1 for <3 contacts using single blocks in rear mounting C13 for <6 contacts using single and double blocks in front mounting			

Main

### Environment

Protective treatment	ТН	
Ambient air temperature for storage	-4070 °C	
Ambient air temperature for operation	-2570 °C	
Electrical shock protection class	Class II conforming to IEC 60536	
IP degree of protection	IP66 conforming to IEC 60529	
NEMA degree of protection	NEMA 13 NEMA 4X	
Resistance to high pressure washer	7000000 Pa at 55 °C, distance : 0.1 m	
IK degree of protection	IK03 conforming to IEC 50102	

Standards	JIS C8201-5-1		
	UL 508		
	EN/IEC 60947-5-1		
	CSA C22.2 No 14		
	EN/IEC 60947-1		
	EN/IEC 60947-5-5		
	EN/IEC 60947-5-4		
	JIS C8201-1		
Product certifications	GL[RETURN]BV[RETURN]LROS (Lloyds register of shipping)		
	[RETURN]CSA[RETURN]DNV[RETURN]UL listed		
Vibration resistance	5 gn (f= 2500 Hz) conforming to IEC 60068-2-6		
Shock resistance	30 gn (duration = 18 ms) for half sine wave acceleration conforming to IEC 60068-2-27		
	50 gn (duration = 11 ms) for half sine wave acceleration conforming to IEC 60068-2-27		

## Offer Sustainability

Sustainable offer status	Green Premium product			
REACh Regulation	REACh Declaration			
REACh free of SVHC	Yes			
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)			
Mercury free	Yes			
China RoHS Regulation	China RoHS Declaration			
RoHS exemption information	<b>₩</b> Yes			
Environmental Disclosure	Product Environmental Profile			
Circularity Profile	End Of Life Information			


## Contractual warranty

Warranty

18 months

Product data sheet Dimensions Drawings **ZB5AFDD** 

## Dimensions






# **ZB5AFDD**

## Panel Cut-out for Pushbuttons, Switches and Pilot Lights (Finished Holes, Ready for Installation)


Connection by Screw Clamp Terminals or Plug-in Connectors or on Printed Circuit Board



- (1) Diameter on finished panel or support
- (2) For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended.
- (3) Ø22.5 mm recommended (Ø22.3  $_0$  <sup>+0.4</sup>) / Ø0.89 in. recommended (Ø0.88 in.  $_0$  <sup>+0.016</sup>)

Connections	a in mm	a in in.	b in mm	b in in.
By screw clamp terminals or plug-in connector	40	1.57	30	1.18
By Faston connectors	45	1.77	32	1.26
On printed circuit board	30	1.18	30	1.18

#### **Detail of Lug Recess**



(1) Diameter on finished panel or support

(2) For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended.

(3) Ø22.5 mm recommended (Ø22.3  $_0$  <sup>+0.4</sup>) / Ø0.89 in. recommended (Ø0.88 in.  $_0$  <sup>+0.016</sup>)

Pushbuttons, Switches and Pilot Lights for Printed Circuit Board Connection

### Life Is On Schneider

#### Panel Cut-outs (Viewed from Installer's Side)



A: 30 mm min. / 1.18 in. min. B: 40 mm min. / 1.57 in. min.

## Printed Circuit Board Cut-outs (Viewed from Electrical Block Side)

Dimensions in mm



A: 30 mm min. B: 40 mm min.

Dimensions in in.



A: 1.18 in. min. B: 1.57 in. min.

#### General Tolerances of the Panel and Printed Circuit Board

The cumulative tolerance must not exceed 0.3 mm / 0.012 in.: T1 + T2 = 0.3 mm max.

#### Installation Precautions

- Minimum thickness of circuit board: 1.6 mm / 0.06 in.
- Cut-out diameter: 22.4 mm ± 0.1 / 0.88 in. ± 0.004
- Orientation of body/fixing collar ZB5AZ009: ± 2°30' (excluding cut-outs marked a and b).
- Tightening torque of screws ZBZ006: 0.6 N.m (5.3 lbf.in) max.
- Allow for one ZB5AZ079 fixing collar/pillar and its fixing screws:
  - every 90 mm / 3.54 in. horizontally (X), and 120 mm / 4.72 in. vertically (Y).
  - with each selector switch head (ZB5AD•, ZB5AJ•, ZB5AG•).

The fixing centers marked a and b are diagonally opposed and must align with those marked 4 and 5.




#### Mounting of Adapter (Socket) ZBZ01•

- 1 2 elongated holes for ZBZ006 screw access
- 2 1 hole Ø 2.4 mm  $\pm$  0.05 / 0.09 in.  $\pm$  0.002 for centring adapter ZBZ01•
- 38 × Ø 1.2 mm / 0.05 in. holes
- 4 1 hole Ø 2.9 mm ± 0.05 / 0.11 in. ± 0.002, for aligning the printed circuit board (with cut-out marked a)
- 5 1 elongated hole for aligning the printed circuit board (with cut-out marked b)
- 6 4 holes Ø 2.4 mm / 0.09 in. for clipping in adapter ZBZ01•

Dimensions An + 18.1 relate to the Ø 2.4 mm ± 0.05 / 0.09 in. ± 0.002 holes for centring adapter ZBZ01•.

**ZB5AFDD** 

Electrical Composition Corresponding to Code C12



Electrical Composition Corresponding to Code C13

Electrical Composition Corresponding to Code C15

1 N/O

1 N/C

1 N/O + N/C or 1 N/O + N/O or 1 N/C + N/C

Electrical Composition Corresponding to Codes C9, C11, SF1 and SR1

Legend

8

Single contact

Double contact

Light block

#### Possible location