

## Product data sheet Characteristics

## **ZB5AW13**

Head for illuminated push button, Harmony XB5, XB4, green projecting pushbutton Ø22 mm spring return BA9s bulb



	Main				
	Range of product	Harmony XB5			
	Product or component	Head for illuminated push-button			
	type				
	Device short name	ZB5			
	Product compatibility	BA 9s			
	Bezel material	Dark grey plastic			
	Mounting diameter	22 mm			
	Sale per indivisible quantity	1			
	Head type	Standard			
	Shape of signaling unit head	Round			
	Type of operator	Spring return			
	Operator profile	Green projecting, unmarked			
	Operator additional information	With plain lens			
Complementary					
CAD overall width	29 mm				
CAD overall height	29 mm				
CAD overall depth	32 mm	32 mm			
Net weight	0.017 kg	0.017 kg			
Resistance to high pressure washer	7000000 Pa at 55 °C, distance : 0.1 m				
Mechanical durability	10000000 cycles				
Main group	Illum push-button	Illum push-button			
Group of product	Projected push BA9s	Projected push BA9s			
Station name	XALD 15 cut-outs XALK 25 cut-outs				
Cap/operator or lens colour	Green				
Marking	Unmarked				
Electrical composition code	M8 for <6 contacts using M9 for <2 contacts using transformer	M7 for <6 contacts using single blocks in front mounting with BA 9s M8 for <6 contacts using single and double blocks in front mounting with BA 9s M9 for <2 contacts using single blocks in front mounting with BA 9s and transformer MF2 for <2 contacts using single blocks in front mounting with BA 9s			
Device presentation	Basic sub-assemblies				
Environment					
Protective treatment	TC				
Ambient air temperature for storage	-4070 °C	-4070 °C			
Ambient air temperature for operation	-4055 °C				
Overvoltage category	Class II conforming to IEC	C 60536			

IP degree of protection

IP69 IP69K

IP66 conforming to IEC 60529

NEMA degree of protection	NEMA 13			
	NEMA 4X			
IK degree of protection	IK05 conforming to EN 50102			
Standards	UL 508			
	EN/IEC 60947-1			
	EN/IEC 60947-5-4			
	CSA C22.2 No 14			
	EN/IEC 60947-5-1			
	JIS C8201-5-1			
	GB 14048.5			
	JIS C8201-1			
Product certifications	CSA[RETURN]DNV[RETURN]GL[RETURN]BV[RETURN]LROS (Lloyds register of shipping)[RETURN]UL listed			
Vibration resistance	5 gn (f= 2500 Hz) conforming to IEC 60068-2-6			
Shock resistance	30 gn (duration = 18 ms) for half sine wave acceleration conforming to IEC 60068-2-27			
	50 gn (duration = 11 ms) for half sine wave acceleration conforming to IEC 60068-2-27			

## Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	4.0 cm
Package 1 Width	6.4 cm
Package 1 Length	3.6 cm
Package 1 Weight	16.0 g
Unit Type of Package 2	S01
Number of Units in Package 2	50
Package 2 Height	15.0 cm
Package 2 Width	15.0 cm
Package 2 Length	40.0 cm
Package 2 Weight	1.028 kg

## Offer Sustainability

Sustainable offer status	Green Premium product		
REACh Regulation	REACh Declaration		
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)		
Mercury free	Yes		
China RoHS Regulation	China RoHS Declaration		
RoHS exemption information	<b>₽</b> Yes		
Environmental Disclosure	Product Environmental Profile		
Circularity Profile	Generation		


## Contractual warranty

Warranty

18 months

Product data sheet Dimensions Drawings ZB5AW13

#### Dimensions






# **ZB5AW13**

#### Panel Cut-out for Pushbuttons, Switches and Pilot Lights (Finished Holes, Ready for Installation)


Connection by Screw Clamp Terminals or Plug-in Connectors or on Printed Circuit Board



- (1) Diameter on finished panel or support
- (2) For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended.
- (3) Ø22.5 mm recommended (Ø22.3  $_0$  <sup>+0.4</sup>) / Ø0.89 in. recommended (Ø0.88 in.  $_0$  <sup>+0.016</sup>)

Connections	a in mm	a in in.	b in mm	b in in.
By screw clamp terminals or plug-in connector	40	1.57	30	1.18
By Faston connectors	45	1.77	32	1.26
On printed circuit board	30	1.18	30	1.18

#### **Detail of Lug Recess**



(1) Diameter on finished panel or support

(2) For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended.

(3) Ø22.5 mm recommended (Ø22.3  $_0$  <sup>+0.4</sup>) / Ø0.89 in. recommended (Ø0.88 in.  $_0$  <sup>+0.016</sup>)

Pushbuttons, Switches and Pilot Lights for Printed Circuit Board Connection

#### Panel Cut-outs (Viewed from Installer's Side)



A: 30 mm min. / 1.18 in. min. B: 40 mm min. / 1.57 in. min.

#### Printed Circuit Board Cut-outs (Viewed from Electrical Block Side)

Dimensions in mm



A: 30 mm min. B: 40 mm min.

Dimensions in in.



A: 1.18 in. min. B: 1.57 in. min.

#### General Tolerances of the Panel and Printed Circuit Board

The cumulative tolerance must not exceed 0.3 mm / 0.012 in.: T1 + T2 = 0.3 mm max.

#### Installation Precautions

- Minimum thickness of circuit board: 1.6 mm / 0.06 in.
- Cut-out diameter: 22.4 mm ± 0.1 / 0.88 in. ± 0.004
- Orientation of body/fixing collar ZB5AZ009: ± 2°30' (excluding cut-outs marked a and b).
- Tightening torque of screws ZBZ006: 0.6 N.m (5.3 lbf.in) max.
- Allow for one ZB5AZ079 fixing collar/pillar and its fixing screws:
  - every 90 mm / 3.54 in. horizontally (X), and 120 mm / 4.72 in. vertically (Y).
  - with each selector switch head (ZB5AD•, ZB5AJ•, ZB5AG•).

The fixing centers marked a and b are diagonally opposed and must align with those marked 4 and 5.




#### Mounting of Adapter (Socket) ZBZ01•


- 1 2 elongated holes for ZBZ006 screw access
- 2 1 hole Ø 2.4 mm  $\pm$  0.05 / 0.09 in.  $\pm$  0.002 for centring adapter ZBZ01•
- 38 × Ø 1.2 mm / 0.05 in. holes
- 4 1 hole Ø 2.9 mm ± 0.05 / 0.11 in. ± 0.002, for aligning the printed circuit board (with cut-out marked a)
- 5 1 elongated hole for aligning the printed circuit board (with cut-out marked b)
- 6 4 holes Ø 2.4 mm / 0.09 in. for clipping in adapter ZBZ01•

Dimensions An + 18.1 relate to the Ø 2.4 mm ± 0.05 / 0.09 in. ± 0.002 holes for centring adapter ZBZ01•.

#### Electrical Composition Corresponding to Codes M1 and M7



Electrical Composition Corresponding to Codes M2 and M8



Electrical Composition Corresponding to Code M9



Electrical Composition Corresponding to Codes M5, M10, MF1, MR1 and MF2



#### Legend



Single contact

Double contact

Light block

#### Possible location