Product data sheet Characteristics

SR2B201JD

compact smart relay Zelio Logic - 20 I O - 12 VDC - clock - display





Main

Range of product	Zelio Logic
Product or component type	Compact smart relay

Complementary

Local display	With		
Number or control scheme lines	0240 with ladder programming 0500 with FBD programming		
Cycle time	690 ms		
Backup time	10 years at 25 °C		
Clock drift	12 min/year at 055 °C 6 s/month at 25 °C		
Checks	Program memory on each power up		
[Us] rated supply voltage	12 V DC		
Supply voltage limits	10.414.4 V		
Maximum supply current	200 mA (without extension)		
Power dissipation in W	2.5 W without extension		
Reverse polarity protection	With		
Discrete input number	12 conforming to IEC 61131-2 Type 1		
Discrete input type	Resistive		
Discrete input voltage	12 V DC		
Discrete input current	4 mA		
Counting frequency	1 kHz for discrete input		
Voltage state 1 guaranteed	>= 7 V for IBIG used as discrete input circuit >= 5.6 V for I1IA and IHIR discrete input circuit		
Voltage state 0 guaranteed	<= 3 V for IBIG used as discrete input circuit <= 2.4 V for I1IA and IHIR discrete input circuit		
Current state 1 guaranteed	>= 2 mA (I1IA and IHIR discrete input circuit) >= 0.5 mA (IBIG used as discrete input circuit)		
Current state 0 guaranteed	<= 0.9 mA (I1IA and IHIR discrete input circuit) <= 0.9 mA (IBIG used as discrete input circuit)		
Input compatibility	3-wire proximity sensors PNP for discrete input		
Analogue input number	6		
Analogue input type	Common mode		
Analogue input range	010 V 012 V		
Maximum permissible voltage	14.4 V for analogue input circuit		
Analogue input resolution	8 bits at maximum voltage		
LSB value	39 mV for analogue input circuit		
Conversion time	Smart relay cycle time for analogue input circuit		

Conversion error	+/- 5 % at 25 °C for analogue input circuit +/- 6.2 % at 55 °C for analogue input circuit		
Repeat accuracy	+/- 2 % at 55 °C for analogue input circuit		
Operating distance	10 m between stations, with screened cable (sensor not isolated) for analogue input circuit		
Input impedance	14 kOhm for IBIG used as analogue input circuit 14 kOhm for IBIG used as discrete input circuit 2.7 kOhm for I1IA and IHIR discrete input circuit		
Number of outputs	8 relay		
Output voltage limits	24250 V AC (relay output) 530 V DC (relay output)		
Contacts type and composition	NO for relay output		
Output thermal current	8 A for all 8 outputs for relay output		
Electrical durability	AC-12: 500000 cycles at 230 V, 1.5 A for relay output conforming to IEC 60947-5-1 AC-15: 500000 cycles at 230 V, 0.9 A for relay output conforming to IEC 60947-5-1 DC-12: 500000 cycles at 24 V, 1.5 A for relay output conforming to IEC 60947-5-1 DC-13: 500000 cycles at 24 V, 0.6 A for relay output conforming to IEC 60947-5-1		
Switching capacity in mA	>= 10 mA at 12 V (relay output)		
Operating rate in Hz	0.1 Hz (at le) for relay output 10 Hz (no load) for relay output		
Mechanical durability	10000000 cycles for relay output		
[Uimp] rated impulse withstand voltage	4 kV conforming to EN/IEC 60947-1 and EN/IEC 60664-1		
Clock	With		
Response time	10 ms (from state 0 to state 1) for relay output 5 ms (from state 1 to state 0) for relay output		
Connections - terminals	Screw terminals, 1 x 0.21 x 2.5 mm² (AWG 25AWG 14) semi-solid Screw terminals, 1 x 0.21 x 2.5 mm² (AWG 25AWG 14) solid Screw terminals, 1 x 0.251 x 2.5 mm² (AWG 24AWG 14) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² (AWG 24AWG 16) solid Screw terminals, 2 x 0.252 x 0.75 mm² (AWG 24AWG 18) flexible with cable end		
Tightening torque	0.5 N.m		
Overvoltage category	III conforming to IEC 60664-1		
Net weight	0.38 kg		

Environment

Immunity to microbreaks	10 ms repeated 20 times		
Product certifications	C-Tick[RETURN]GL[RETURN]UL[RETURN]CSA[RETURN]GOST		
Standards	IEC 60068-2-6 Fc IEC 61000-4-11 IEC 61000-4-5 IEC 61000-4-2 level 3 IEC 61000-4-6 level 3 IEC 61000-4-4 level 3 IEC 61000-4-7 IEC 61000-4-12 IEC 60068-2-27 Ea IEC 61000-4-3		
IP degree of protection	IP20 (terminal block) conforming to IEC 60529 IP40 (front panel) conforming to IEC 60529		
Environmental characteristic	EMC directive conforming to IEC 61000-6-2 EMC directive conforming to IEC 61000-6-3 EMC directive conforming to IEC 61000-6-4 EMC directive conforming to IEC 61131-2 zone B Low voltage directive conforming to IEC 61131-2		
Disturbance radiated/conducted	Class B conforming to EN 55022-11 group 1		
Pollution degree	2 conforming to IEC 61131-2		
Ambient air temperature for operation	-2040 °C in non-ventilated enclosure conforming to IEC 60068-2-1 and IEC 60068-2-2 -2055 °C conforming to IEC 60068-2-1 and IEC 60068-2-2		
Ambient air temperature for storage	-4070 °C		
Operating altitude	2000 m		

Maximum altitude transport	3048 m		
Relative humidity	95 % without condensation or dripping water		
Packing Units			
Unit Type of Package 1	PCE		
Number of Units in Package 1	1		
Package 1 Height	6.86 cm		
Package 1 Width	10.16 cm		
Package 1 Length	13.46 cm		
Package 1 Weight	0.36 kg		
Unit Type of Package 2	S03		
Number of Units in Package 2	20		
Package 2 Height	30 cm		
Package 2 Width	30 cm		
Package 2 Length	40 cm		
Package 2 Weight	7.811 kg		
T dokage 2 Weight	7.011 kg		
Offer Sustainability			
Sustainable offer status	Green Premium product		
REACh Regulation	REACh Declaration		
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)		
Mercury free	Yes		
China RoHS Regulation	China RoHS Declaration		
RoHS exemption information	⊈ Yes		
Environmental Disclosure	Product Environmental Profile		
Circularity Profile	End Of Life Information		
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins		
PVC free	Yes		


Contractual warranty

Contractad Warranty		
Warranty	18 months	

SR2B201JD


Compact and Modular Smart Relays

Mounting on 35 mm/1.38 in. DIN Rail




(1) With SR2USB01 or SR2BTC01

Screw Fixing (Retractable Lugs)




(1) With SR2USB01 or SR2BTC01

Position of Display




Compact and Modular Smart Relays

Connection of Smart Relays on DC Supply



- (1) 1 A quick-blow fuse or circuit-breaker.
- (2) Fuse or circuit-breaker.
- (3) Inductive load.
- (4) Q9 and QA: 5 A (max. current in terminal C: 10 A).

Discrete Input Used for 3-Wire Sensors



(1) 1 A quick-blow fuse or circuit-breaker.


SR2B201JD

Compact and Modular Smart Relays

Electrical Durability of Relay Outputs

(in millions of operating cycles, conforming to IEC/EN 60947-5-1)

DC-12 (1)




X: Current (A)

Y: Millions of operating cycles

(1) DC-12: control of resistive loads and of solid state loads isolated by opto-coupler, $L/R \le 1$ ms.

DC-13 (1)



X: Current (A)

Y: Millions of operating cycles

(1) DC-13: switching electromagnets, $L/R \le 2 \times (Ue \times Ie)$ in ms, Ue: rated operational voltage, Ie: rated operational current (with a protection diode on the load, DC-12 curves must be used with a coefficient of 0.9 applied to the number in millions of operating cycles).