XMLR100M2P05

Pressure sensors XMLR 100bar - G 1/4 - 24VDC - 2xPNP - M12



Main Range

Range of product	Telemecanique Pressure sensors XM
Product or component type	Electronic pressure sensors
Pressure sensor type	Pressure transmitter
Pressure switch type of operation	Pressure switch with 2 switching outputs
Device short name	XMLR
Pressure rating	9997.40 KPa 100 bar
Maximum permissible accidental pressure	300 Bar 30 MPa 29992.19 kPa
Destruction pressure	600 Bar 59984.39 KPa 60 MPa
Controlled fluid	Fresh water (080 °C) Air (-2080 °C) Hydraulic oil (-2080 °C) Refrigeration fluid (-2080 °C)
Fluid connection type	G 1/4 (female) conforming to DIN 3852-Y
[Us] rated supply voltage	24 V DC SELV (voltage limits: 1733 V)

Complementary

<= 50 mA
Male connector M12, 4 pins
Discrete
Solid state PNP, 2 NO/NC programmable
250 mA
2 NO/NC programmable
Fixed differential
2 V
799.799997.40 KPa 0.810 MPa 8100 bar
499.879700.92 KPa 597 Bar 0.597 MPa
299.92 KPa 0.3 MPa 3 bar
316L stainless steel
Polyester
316L stainless steel Polyacrylamide
Any position, but disposals can falsified the measurement in case of upside down mounting
Overload protection Reverse polarity Short-circuit protection Overvoltage protection
<= 5 ms for discrete output
050 s in steps of 1 second
4 digits 7 segments

Local signalling	2 LEDs (yellow) for light ON when switch is actuated
Display response time type	Fast 50 ms Normal 200 ms Slow 600 ms
Maximum delay first up	300 ms
Overall accuracy	<= 1 % of the measuring range
Measurement accuracy on switching output	<= 0.6 % of the measuring range
Repeat accuracy	<= 0.2 % of the measuring range
Drift of the sensitivity	+/- 0.03 % of measuring range/°C
Drift of the zero point	+/- 0.1 % of measuring range/°C
Display accuracy	<= 1 % of the measuring range
Mechanical durability	10000000 cycles
Depth	42 mm
Height	88 mm
Width	41 mm
Net weight	0.186 kg
[Uimp] rated impulse withstand voltage	0.5 kV DC
Electromagnetic compatibility	Susceptibility to electromagnetic fields: 10 V/m 802000 MHz conforming to IEC 61000-4-3 Immunity to conducted RF disturbances: 10 V 0.1580 MHz conforming to IEC 61000-4-6 Surge immunity test: 1 kV conforming to IEC 61000-4-5 Electrical fast transient/burst immunity test: 2 kV conforming to IEC 61000-4-4 Electrostatic discharge immunity test: 8 kV air, 4 kV contact conforming to IEC 61000-4-2

Environment

2. It will britte	
Marking	CE
Product certifications	cULus
Standards	UL 61010-1 IEC 61326-2-3
Ambient air temperature for operation	-2080 °C
Ambient air temperature for storage	-4080 °C
IP degree of protection	IP65 conforming to IEC 60529 IP67 conforming to IEC 60529
Vibration resistance	20 gn (f= 102000 Hz) conforming to IEC 60068-2-6
Shock resistance	50 gn conforming to IEC 60068-2-27

Packing Units

i doking office	
Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	6.500 cm
Package 1 Width	7.500 cm
Package 1 Length	13.000 cm
Package 1 Weight	184.000 g
Unit Type of Package 2	S02
Number of Units in Package 2	20
Package 2 Height	15 cm
Package 2 Width	30 cm
Package 2 Length	40 cm
Package 2 Weight	4.020 kg


Offer Sustainability

REACh Regulation	REACh Declaration
REACh free of SVHC	Yes
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
Mercury free	Yes
RoHS exemption information	€Yes

Product data sheet Dimensions Drawings

XMLR100M2P05

Dimensions




(1) Fluid entry: G 1/4 A female

Product data sheet Connections and Schema

XMLR100M2P05

Connections and Schema


Connector Wiring



XMLR100M2P05

Switching Output Description. Hysteresis Mode

The hysteresis switching mode is typically used for the "pumping and/or emptying applications".




X: Time Y: Pressure (1) Output

NP: Nominal Pressure

SP: Set point (adjustable from 8 % to 100 % NP) rP: Reset point (adjustable from 5 % to 97 % NP)

Switching Output Description. Window Mode

The window switching mode is typically used for the "pressure regulation applications"



X: TimeY: Pressure(1) OutputNP: Nominal pressure


 $FH:\ High\ switching\ point\ (adjustable\ from\ 8\ \%\ to\ 100\ \%\ NP)$

FL: Low switching point (adjustable from 5 % to 97 % NP)

Switching Output Description. Time Delay

The Time Delay is typically used to filter out the fast pressure transients.

The output only switches after a time "dS" and "dr" adjustable from 0 to 50 seconds.



X: Time
Y: Pressure
(1) Output
SP: Set point
rP: Reset point
dS: Time delay on the set point
dr: Time delay on the reset point